# LBB 1996/00 Plena Voice Alarm Remote Control

www.boschsecurity.com





- ▶ Remote control of the voice alarm system
- ▶ EN 54-16 certified and EN 60849 compliant
- Emergency (EMG) microphone and background (BGM) zone selections
- ▶ EMG state and fault indicators
- ► Call monitoring loudspeaker

The Plena voice alarm remote control panels allow the system to be controlled remotely from one or two remote locations. There are five models available:

- The fireman's panel, which has oversized, illuminated controls and an all-call function
- The main RC unit, which duplicates the front panel of the Voice Alarm Controller
- The RC extension, which duplicates the front panel of the router
- The main RC kit
- · The RC extension kit

The kits are a functional match to the remote control and the RC extension, with connectors on the front panel instead of controls and indicators.

#### **Functions**

The remote control is an exact duplicate of the control panel on the LLB 1990/00 Plena Voice Alarm System Controller. The LBB 1996/00 provides all EVAC control from one or two locations, such as at entrance points. The remote control has BGM and emergency-call zone selection without source, volume or tone control.

It is possible to enter or acknowledge the emergency state, and acknowledge and reset the fault state. Emergency or alert messages can be started, and live calls can be made.

An LED meter shows the presence and level of the calls that are running in the system. The fault indicators reflect any faults present in the system. The unit connects to the Plena Voice Alarm System via standard shielded CAT 5 cable. The included rack mounting brackets can also mount the unit on a wall with spacing for cables at the back, as well as to a horizontal surface above or below the unit.

#### **Certifications and approvals**

Safety	acc. to EN 60065
Immunity	acc. to EN 50130-4
Emission	acc. to EN 55103-1
Emergency	acc. to EN 54-16 / EN 60849

# 2 | LBB 1996/00 Plena Voice Alarm Remote Control

Region	Certification	
Europe	CE	Declaration of Conformity
	CPD	
Poland	CNBOP	

# Installation/configuration notes



LBB 1996/00 rear view

## Parts included

Quantity	Component
1	LBB 1996/00 Plena Voice Alarm System Remote Control
1	Set of 19" mounting brackets
1	EMG microphone and cable
1	EMG microphone mounting clip
1	1 m CAT 5 cable

# **Technical specifications**

## Electrical

Power supply	
Voltage	24 VDC, +15% / -15%
Current typical	100 mA
Current max (indicator test)	250 mA
Relay contacts	30 V, 1 A

### Mechanical

Dimensions (H x W x D)	134 x 430 x 90 mm (19" wide, 3U high)
Weight	Approx. 3 kg
Mounting	19" rack or wall
Color	Charcoal

#### **Environmental**

Operating temperature	-10 °C to +55 °C (14 °F to +131 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

## **Ordering information**

**LBB 1996/00 Plena Voice Alarm Remote Control** six-zone voice alarm remote control with microphone Order number **LBB1996/00** 

#### Represented by:

#### Americas:

Americas: Bosch Security Systems, Inc. 12000 Portland Avenue South Burnsville MN 55337, USA Phone: +1-800-392-3497 Fax: +1-800-955-6831 audiosupport@us.bosch.com www.boschsecurity.com

## Europe, Middle East, Africa:

Bosch Security Systems B.V. P.O. Box 80002 P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

#### Asia-Pacific:

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

#### China:

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398 www.boschsecurity.com.cn

#### America Latina:

America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
al.securitysystems@bosch.com
www.boschsecurity.com